



SPECIFICATIONS											
WIRING	INPUT		OUTPUT				SHAFT ROTATION TO INCREASE VOLTAGE	TERMINAL CONNECTIONS			
	VOLTS	HERTZ	VOLTS	CONSTANT CURRENT LOAD		CONSTANT IMPEDANCE LOAD		FOR INCREASING VOLTAGE AS VIEWED FROM BASE END			
				MAX. AMPS	MAX. KVA	MAX. AMPS		MAX. KVA	INPUT	JUMPER	OUTPUT
SINGLE PHASE	120	60	0-120	12	1.44	15	1.80	CW	1-4	---	4-3
								CCW	1-4	---	1-3

  

UNLESS OTHERWISE SPECIFIED, TOLERANCE IS ±	DECIMALS	HOLES	ANGLES	DRAFT	UNITS	TITLE: SPEC. CONTROL DRAWING VARIABLE TRANSFORMER MODEL: 1210B				
	.XX	.003	1°	1-1/2°	IN [mm]					
MATERIAL:					ALL DIMENSIONS APPLY AFTER PLATING	DRAWN BY: S.A. SMITH CHECKER: ENGINEER:	DATE: 9/24/97 DATE: DATE:	FIRST USED ON: SCALE: 10 LBS SCALE: 1=1	DO NOT SCALE DWG.: 83008 SHEET 1 OF 1	DWG. NO.: 031-2960